

VictorSoft 1.5x1.5 Square LED Studio Lights Bi-color Dimmable Ultra Bright

Basic Information

- Place of Origin:
- Brand Name: LS
- Certification: CE, RoHS
- Model Number:
- Minimum Order Quantity:
- Price:
 - Packaging Details:
 - Delivery Time: 10-45 work days
 - Payment Terms: T/T

China

20

V-3000ASVL

Negotiation

2 pcs per cartons

Supply Ability: 500pcs per month



Product Name: VictorSoft 1.5x1.5 Model No.: V-3000ASVL • Material: Alluminum Alloy • Size: 61.5x70.5x9cm • Weight: 10.46kg (23lb) • CRI: ≥96 • Voltage: AC100-240V, DC24-30V 120° • Beam Angle: • Highlight: photography studio light



More Images





VictorSoft 1.5x1.5 Square LED Studio Light Bi-color Dimmable Ultra Bright

Product Specifications

LED Light Source	LEDs
Color temperature	3200±150K~5600K±300K
Brightness/Light Intensity	5180Lux/m, 1458Lux/2m
Power draw	200W
Beam angle	120°wide beam
CRI	≥96
Lamp Lifetime	50,000 hrs
Working Voltage	AC100-240V, DC24-30V
External Power	Sony V-mount battery plate or AB plate
Mount	Yoke with standard pin receiver baby 5/8"
Dimension	61.5x70.5x9cm
Weight	10.46kg (23lb)

Standard set Includied

1 x Victor 1.5x1.5 (V-3000ASVL)

- 1 x Barndoor 1 x Yoke
- 1 x AC power adapter
- 1 x Power Cord
- 1 x DMX cable
- 1 x Safety cable

Optional accessories:

Honeycomb Grid Bag for one light



Main Features

VictorSoft (strong and soft) that no additional diffusor need. Power draw 100W via AC power adatper or V-lock broadcating battery Removabe, clip-in 4-way barndoor, provided with the light. Bi-color 3200K to 5600K, from Tungsten to Daylight variable. High CRI of 96 and above. 120° wide beam, flicker free. Rear LCD display of the brightness and color temperature. Metal construction and traditional 1x1 size

Easy to operate when out of the box, used for both studio or location work as a photo light.

VictorSoft 1.5x1.5 V-3000ASVL is a powerful soft light. It draws 200W and gives a rather beautiful and strong but soft light beam with no hotspots and multiple showdows that a traditional LED light may have.

It is the chip LEDs that the light use. It has a wider beam angle 120 degree than the 30-60 degree of traditional dot LED lights have. It gives a much wider shooting area. It gives a much wider shooting area. And with the provided barndoor and the optional honeycomb grid, the light beam can be controlled in a different way.

The light has a built-in diffusor that people do not need to use additonal white diffusors. It becomes so easy to operate when out of the box. Put it on a light stand, clip in the barndoor and then power the light with the provided AC power adatper and power cord. Or use it in the Studio with the DMX function of the light.



Cautions:

1. It is no need to replace the LED bulbs in normal use.Please do not disassemble the light or solder the LED bulbs by the non-professionals.

- 2. Please do take off the batteries when in storage.
- 3. Please do not block the louvers, or it may seriously influence LEDs' effect and lifetime.
- 4. The charger adapter is used for battery charging only. Please do not use on the light directly.
- 5. Please do discharge and recharge the battery at least once for every month if it is not in use.
- 6. It is not allowed to drop or impact the light to avoid fire.
- It is not allowed to short circuit the battery, or it may seriously damage the battery or cause a fire.
- 8. It is not allowed to throw the battery into fire.

Warranty:

The LED light is guaranteed for 12 months.

SOLAR SLIGHT Beijing Silk Road Enterprise Management Services Co.,LTD

C 17733330123 C miclecleanmo@gmail.com C solarpanelstreetlight.com

No 41, Dongsihuan Zhong Road, Chaoyang District, Beijing, 100025, P.R.C